

## *Positive Voltage Regulator*

---

---

### *ML62 Series Specification*

---

---

## **ML62 Series** **Positive Voltage Regulator**

### ❖ **Application**

- ◆ *Battery Powered Equipment*
- ◆ *Palmtops*
- ◆ *Portable Cameras and Video Recorders*
- ◆ *Reference Voltage Sources*

### ❖ **Features**


- CMOS Low Power Consumption :  
Typical 3.3uA at V<sub>out</sub>=5.0V
- Output Voltage Range : 2.0V to 6.0V in 0.1V increments
- Highly Accurate : Output Voltage  $\pm 2\%$
- Maximum Output Current: 250mA  
(within the maximum power dissipation, V<sub>out</sub>=5.0V)
- Small Input-Output Voltage Differential :  
0.12V at 100mA and 0.38V at 200mA
- Input stability : Typ. 0.2%/V
- Package Available :  
SOT- 23 (150mW), SOT- 89 (500mW) & TO- 92 (300mW)

### ❖ **General Description**

The ML62 is a group of positive voltage output, three-pin regulator which provides high output current even when the input/output voltage differential is small.

The ML62 consists of a high-precision voltage reference, an error correction circuit, and a current limited output driver.

### ❖ **Block Diagram**




### ❖ **Absolute Maximum Ratings**

Parameter		Symbol	Ratings	Units
Input Voltage		V <sub>IN</sub>	12	V
Output Current		I <sub>OUT</sub>	500	mA
Output Voltage		V <sub>OUT</sub>	V <sub>SS</sub> -0.3 ~ V <sub>IN</sub> +0.3	V
Continuous Total Power Dissipation	SOT-23	P <sub>d</sub>	150	mW
	SOT-89		500	
	TO-92		300	
Operating Ambient Temperature		T <sub>opr</sub>	-30 ~ +70	°C
Storage Temperature		T <sub>stg</sub>	-30 ~ +70	°C

## ❖ Pin Configuration

SOT-23 :


Pin Number	Pin Name	Description
1	VSS	Ground
2	VOUT	Supply Voltage Output
3	VIN	Supply Voltage Input



SOT-23 (Top View)

SOT-89 :


Pin Number	Pin Name	Description
1	VSS	Ground
2	VIN	Supply Voltage Input
3	VOUT	Supply Voltage Output



SOT-89 (Top View)

TO-92 :

Pin Number	Pin Name	Description
1	VSS	Ground
2	VIN	Supply Voltage Input
3	VOUT	Supply Voltage Output



TO92 (Front View)


## ❖ *Standard Circuit*

### Note on Use


- Oscillation may occur as a result of the impedance present between the power supply and the IC's input. Please use a capacitor (CIN) of at least 1uF, when the impedance is 10 ohm or more.  
With a large output current, Voltage output can be stabilised by increasing capacitor (CIN) size. If CIN is small and capacitor (CL) size is increased, oscillation may occur. In such cases, Voltage output can be stabilised by either increasing the size of CIN or decreasing the size of CL.
- Please ensure that output current (IOUT) is less than  $P_d / (V_{IN} - V_{OUT})$  and does not exceed the stipulated Continuous Total Power Dissipation value ( $P_d$ ).

## ❖ *Test Circuit*

**Test Circuit 1**



**Test Circuit 2**



## ❖ Electrical Characteristics

### ML62502 $V_{OUT}(T)=5.0V$ (Note 1)

Parameter	Symbol	Conditions	Min	Typ	Max	Units	Circuit
Output Voltage	$V_{OUT}(E)$ (Note 2)	$I_{OUT}=40mA$ $V_{IN}=6.0V$	4.900	5.000	5.100	V	1
Maximum Output Current	$I_{OUT\ max}$	$V_{IN}=6.0V$ , $V_{OUT}(E) \approx 4.5V$	250			mA	1
Load Stability	$DV_{OUT}$	$V_{IN}=6.0V$ , $1mA \leq I_{OUT} \leq 100mA$		40	80	mV	1
Input –Output Voltage Differential (Note 3)	$V_{dif1}$	$I_{OUT}=100mA$		120	400	mV	1
	$V_{dif2}$	$I_{OUT}=200mA$		380	750	mV	1
Supply Current	$I_{SS}$	$V_{IN}=6.0V$		3.3	4.5	uA	2
Input Stability	$\frac{DV_{OUT}}{DV_{IN} * V_{OUT}}$	$I_{OUT}=40mA$ $6.0V \leq V_{IN} \leq 10.0V$		0.2	0.3	%V	1
Input Voltage	$V_{IN}$				10	V	-

### ML62402 $V_{OUT}(T)=4.0V$ (Note 1)

Parameter	Symbol	Conditions	Min	Typ	Max	Units	Circuit
Output Voltage	$V_{OUT}(E)$ (Note 2)	$I_{OUT}=40mA$ $V_{IN}=5.0V$	3.920	4.000	4.080	V	1
Maximum Output Current	$I_{OUT\ max}$	$V_{IN}=5.0V$ , $V_{OUT}(E) \approx 3.6V$	200			mA	1
Load Stability	$DV_{OUT}$	$V_{IN}=5.0V$ , $1mA \leq I_{OUT} \leq 100mA$		45	90	mV	1
Input –Output Voltage Differential (Note 3)	$V_{dif1}$	$I_{OUT}=90mA$		170	400	mV	1
	$V_{dif2}$	$I_{OUT}=180mA$		400	750	mV	1
Supply Current	$I_{SS}$	$V_{IN}=5.0V$		3.0	4.5	uA	2
Input Stability	$\frac{DV_{OUT}}{DV_{IN} * V_{OUT}}$	$I_{OUT}=40mA$ $5.0V \leq V_{IN} \leq 10.0V$		0.2	0.3	%V	1
Input Voltage	$V_{IN}$				10	V	-

### ML62302 $V_{OUT}(T)=3.0V$ (Note 1)

Parameter	Symbol	Conditions	Min	Typ	Max	Units	Circuit
Output Voltage	$V_{OUT}(E)$ (Note 2)	$I_{OUT}=40mA$ $V_{IN}=4.0V$	2.940	3.000	3.060	V	1
Maximum Output Current	$I_{OUT\ max}$	$V_{IN}=4.0V$ , $V_{OUT}(E) \approx 2.7V$	150			mA	1
Load Stability	$DV_{OUT}$	$V_{IN}=4.0V$ , $1mA \leq I_{OUT} \leq 80mA$		45	90	mV	1
Input –Output Voltage Differential (Note 3)	$V_{dif1}$	$I_{OUT}=80mA$		180	450	mV	1
	$V_{dif2}$	$I_{OUT}=150mA$		400	850	mV	1
Supply Current	$I_{SS}$	$V_{IN}=4.0V$		2.8	4.5	uA	2
Input Stability	$\frac{DV_{OUT}}{DV_{IN} * V_{OUT}}$	$I_{OUT}=40mA$ $4.0V \leq V_{IN} \leq 10.0V$		0.2	0.3	%V	1
Input Voltage	$V_{IN}$				10	V	-

### ML62202 $V_{OUT}(T)=2.0V$ (Note 1)

Parameter	Symbol	Conditions	Min	Typ	Max	Units	Circuit
Output Voltage	$V_{OUT}(E)$ (Note 2)	$I_{OUT}=40mA$ $V_{IN}=3.0V$	1.960	2.000	2.040	V	1
Maximum Output Current	$I_{OUT\ max}$	$V_{IN}=3.0V$ , $V_{OUT}(E) \approx 1.8V$	100			mA	1
Load Stability	$DV_{OUT}$	$V_{IN}=3.0V$ , $1mA \leq I_{OUT} \leq 60mA$		45	90	mV	1
Input –Output Voltage Differential (Note 3)	$V_{dif1}$	$I_{OUT}=60mA$		180	450	mV	1
	$V_{dif2}$	$I_{OUT}=100mA$		400	850	mV	1
Supply Current	$I_{SS}$	$V_{IN}=3.0V$		2.5	4.5	uA	2
Input Stability	$\frac{DV_{OUT}}{DV_{IN} * V_{OUT}}$	$I_{OUT}=40mA$ $3.0V \leq V_{IN} \leq 10.0V$		0.2	0.3	%V	1
Input Voltage	$V_{IN}$				10	V	-

Note : 1.  $V_{OUT}(T)$  = Specified Output Voltage.

2.  $V_{OUT}(E)$  = Effective Output Voltage (i.e. the output voltage when  $(V_{OUT}(T)+1.0V)$  is provided at the  $V_{IN}$  pin while maintaining a certain  $I_{OUT}$  value).

3.  $V_{dif} = V_{IN1}(\text{Note 4}) - V_{OUT}(E)$

4.  $V_{IN1}$  = The input voltage at the time 98% of  $V_{OUT}(E)$  is output (input voltage has been gradually reduced).

### ❖ Electrical Characteristics by Output Voltage

Part Number	Output voltage				Max Output Current		Load Stability			I-O Voltage Differential		
	V <sub>OUT</sub> (V)				I <sub>OUT max</sub> (mA)		D V <sub>OUT</sub> (mV)			V <sub>diff</sub> (mV)		
	Conditions	MIN.	TYP.	MAX.	Conditions	MIN.	Conditions	TYP.	MAX.	Conditions	TYP.	MAX.
ML62202	I <sub>OUT</sub> =40mA V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V	1.960	2.000	2.040	V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V V <sub>OUT</sub> (E)≥ V <sub>OUT</sub> (T)*0.9	100	V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V 1mA≤I <sub>OUT</sub> ≤60mA	45	90	I <sub>OUT</sub> =60mA	180	450
ML62212		2.058	2.100	2.142								
ML62222		2.156	2.200	2.244								
ML62232		2.254	2.300	2.346								
ML62242		2.352	2.400	2.448								
ML62252		2.450	2.500	2.550								
ML62262		2.548	2.600	2.652								
ML62272		2.646	2.700	2.754								
ML62282		2.744	2.800	2.856								
ML62292		2.842	2.900	2.958								
ML62302		2.940	3.000	3.060		150	V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V 1mA≤I <sub>OUT</sub> ≤80mA	45	90	I <sub>OUT</sub> =80mA	180	450
ML62312		3.038	3.100	3.162								
ML62322		3.136	3.200	3.264								
ML62332		3.234	3.300	3.366								
ML62342		3.332	3.400	3.468								
ML62352		3.430	3.500	3.570								
ML62362		3.528	3.600	3.672								
ML62372		3.626	3.700	3.774								
ML62382		3.724	3.800	3.876								
ML62392		3.822	3.900	3.978		200	V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V 1mA≤I <sub>OUT</sub> ≤100mA	45	90	I <sub>OUT</sub> =90mA	170	400
ML62402		3.920	4.000	4.080								
ML62412		4.018	4.100	4.182								
ML62422		4.116	4.200	4.284								
ML62432		4.214	4.300	4.386								
ML62442		4.312	4.400	4.488								
ML62452		4.410	4.500	4.590								
ML62462		4.508	4.600	4.692								
ML62472		4.606	4.700	4.794								
ML62482		4.704	4.800	4.896								
ML62492		4.802	4.900	4.998		250	V <sub>IN</sub> =V <sub>OUT</sub> +1V 1mA≤I <sub>OUT</sub> ≤100mA	40	80	I <sub>OUT</sub> =100mA	120	400
ML62502		4.900	5.000	5.100								
ML62512		4.998	5.100	5.202								
ML62522		5.096	5.200	5.304								
ML62532		5.194	5.300	5.406								
ML62542		5.292	5.400	5.508								
ML62552		5.390	5.500	5.610								
ML62562		5.488	5.600	5.712								
ML62572		5.586	5.700	5.814								
ML62582		5.684	5.800	5.916								
ML62592		5.782	5.900	6.018								
ML62602		5.880	6.000	6.120								

Part Number	I-O Voltage Differential			Supply Current			Input Stability			Input Voltage
	V <sub>diff2</sub> (mV)			I <sub>SS</sub> (uA)			D V <sub>OUT</sub> /(D V <sub>IN</sub> *V <sub>OUT</sub> ) (%V)			V <sub>IN</sub> (V)
	Conditions	TYP.	MAX.	Conditions	TYP.	MAX.	Conditions	TYP.	MAX.	MAX.
ML62202	I <sub>OUT</sub> =100mA	400	850	V <sub>IN</sub> =V <sub>OUT</sub> (T)+1V	2.5	4.5	I <sub>OUT</sub> =40mA V <sub>OUT</sub> (T)+1V≤V <sub>IN</sub> ≤10V	0.2	0.3	10
ML62212										
ML62222										
ML62232										
ML62242										
ML62252										
ML62262										
ML62272										
ML62282										
ML62292										
ML62302	I <sub>OUT</sub> =150mA	400	850		2.8	4.5				
ML62312										
ML62322										
ML62332										
ML62342										
ML62352										
ML62362										
ML62372										
ML62382										
ML62392										
ML62402	I <sub>OUT</sub> =180mA	400	750		3.0	4.5				
ML62412										
ML62422										
ML62432										
ML62442										
ML62452										
ML62462										
ML62472										
ML62482										
ML62492										
ML62502	I <sub>OUT</sub> =200mA	380	750		3.3	4.5				
ML62512										
ML62522										
ML62532										
ML62542										
ML62552										
ML62562										
ML62572										
ML62582										
ML62592										
ML62602										

## ❖ Ordering Information


Designator	Description
a	<b>Output Voltage</b> eg. 30=3.0V 50=5.0V
b	<b>Output Voltage Accuracy</b> 2 = $\pm 2.0\%$
c	<b>Package Type</b> M = SOT-23 P = SOT-89 T = TO-92
d	<b>Device Orientation</b> R = Embossed Tape (Orientation of Device : Right) L = Embossed Tape (Orientation of Device : Left) B = Bag (TO-92) H = Paper Tape (TO-92)

ML62xxxxx  
t t t t  
a bcd

## ❖ Marking


### SOT-23 :

Designator	Description
1	<b>Type</b> R = Positive Voltage Regulator
2,3	<b>Output Voltage</b> eg. 30 = 3.0V
4	<b>Internal Code</b>




### SOT-89 :

Designator	Description
1	<b>Type</b> R = Positive Voltage Regulator
2,3	<b>Output Voltage</b> eg. 30 = 3.0V
4	<b>Output Voltage Accuracy</b> 2 = $\pm 2.0\%$
5	<b>Internal Code</b>



### TO-92 :


Designator	Description
1	<b>Type</b> R = Positive Voltage Regulator
2,3	<b>Output Voltage</b> eg. 30 = 3.0V
4	<b>Output Voltage Accuracy</b> 2 = $\pm 2.0\%$
5	<b>Internal code</b>
6, 7	<b>Year Code</b> eg. 00 = Year 2000
8, 9	<b>Week Code</b> eg. 10 = Week 10






## ❖ Packaging Information


SOT-23 :



SOT-89 :




TO-92 :




Units : mm

## ❖ Recommended Pattern Layout

SOT-23 :




SOT-89 :



## ❖ Tape and Reel Information



SOT-23 :




	SIZE (mm)
A	$\varnothing 178 \pm 0.8$
B	$2 \pm 0.2$
C	$\varnothing 13 \pm 0.2$
D	$\varnothing 21 \pm 0.8$
G	$8 \pm 0.5$
H	$\varnothing 60$

3,000 pcs / reel

SOT-23 Taping Specifications :




"R" type [Orientation of Device: Right]  
Standard Type



"L" type [Orientation of Device: Left]  
Reverse Type



SOT-89 :




	SIZE (mm)
A	$\varnothing 178 \pm 0.8$
B	$2 \pm 0.2$
C	$\varnothing 13 \pm 0.2$
D	$\varnothing 21 \pm 0.8$
G	$12 \pm 0.5$
H	$\varnothing 60$

1,000 pcs / reel

SOT-89 Taping Specifications :




"R" type [Orientation of Device: Right]  
Standard Type



"L" type [Orientation of Device: Left]  
Reverse Type

TO-92 Taping Specifications :



	SIZE (mm)
P	$12.7 \pm 1.0$
PO	$12.7 \pm 0.3$
P2	$6.35 \pm 0.4$
F	$2.5^{+0.45}_{-0.15}$
W	$18.0 \pm 1.0$
WO	$6.0 \pm 0.3$
W1	$9.0 \pm 0.5$
W2	0.5 MAX
H	$19.0 \pm 0.5$
H0	$16.0 \pm 0.5$
H1	32.25 MAX
D	$\varnothing 4.0 \pm 0.2$
t	$0.6 \pm 0.2$
L1	3.5 MIN

2,000 pcs / box

❖ *History of Revision*

REV	DESCRIPTION	DATE
	First Official Specification	04/04/01
A	SOT-23, SOT-89 & TO-92 Package and packing description added. Operating and Storage Temperature modified.	23/10/01
B	Absolute Maximum Input Rating of Input Voltage increased from 10V to 12V.	02/08/02